

## MINI motion sensor 360°

Marka: Orno | Symbol: OR-CR-263 | Ean: 5900378654773

**ORNO**

### PRODUCT DESCRIPTION

This small motion sensor is used to automatically control lighting or other electric appliances. The device is equipped with potentiometers to adjust lighting time and light intensity. It is compatible with LED diodes.

## TECHNICAL DATA

### General information:

|                                              |                                             |
|----------------------------------------------|---------------------------------------------|
| Max. load:                                   | 400                                         |
| Max. load of the LED light source:           | 100 W                                       |
| Degree of protection (IP):                   | 20                                          |
| Relay output:                                | Yes                                         |
| Nominal voltage:                             | 230V~, 50Hz                                 |
| Presence detector:                           | No                                          |
| Colour:                                      | white                                       |
| Installation:                                | surface mounting                            |
| Dimensions of the sensor - width (mm):       | Ø76 mm                                      |
| Dimensions of the sensor - height (mm):      | Ø76 mm                                      |
| Dimensions of the sensor - depth (mm):       | 20.2 mm                                     |
| Detection angle:                             | 360°                                        |
| Type of sensor:                              | Infrared                                    |
| Detection range:                             | Ø8m m                                       |
| Adjustable daylight sensor (LUX):            | Yes                                         |
| Daylight sensor adjustment range (LUX):      | <3–2000lux                                  |
| Adjustable time setting (TIME):              | Yes                                         |
| Lighting time adjustment range (TIME):       | min: 10 sek. ± 3 sek.; max: 7 min. ± 2 min. |
| Adjustment of motion detection range (SENS): | No                                          |

