

Lamp bulb socket with PIR motion sensor, 360°, IP20, E27 holder, 1x60W

Marka: **Virone** | Symbol: **MS-2** | Ean: **5908254816994**

ViRONE

PRODUCT DESCRIPTION

The socket is used for automatic lighting control. Its task is to turn on and off the light source installed in the socket. No installation is required. Possible adjustment: time setting after motion detection and daylight sensor.

TECHNICAL DATA

General information:

Max. load:	60 W
Max. load of the LED light source:	15 W
Degree of protection (IP):	20
Relay output:	No
Presence detector:	No
Working temperature:	-20~+40
Daylight sensor adjustment range (LUX):	<3–2000lux
Adjustable daylight sensor (LUX):	Yes
Installation:	bulb socket
Detection range:	Ø6 m
Dimensions of the sensor - width (mm):	Ø50 mm
Dimensions of the sensor - height (mm):	Ø50 mm
Dimensions of the sensor - depth (mm):	130 mm
Colour:	white
Nominal voltage:	230V~, 50Hz
Detection angle:	360°
Type of sensor:	Infrared
Lighting time adjustment range (TIME):	min: 10 sek. ± 3 sek.; max: 5 min. ± 1 min.
Adjustment of motion detection range (SENS):	No
Adjustable time setting (TIME):	Yes

