

# PRODUCT CARD



PRODUCT CODE: OR-CR-261

EAN CODE: 5900378654742

## Motion sensor for installation box, 160°, IP20

This motion sensor is used to automatically control lighting or other electric appliances. It operates based on a two-wire system and can be flush-mounted inside an installation box of Ø60 mm diameter. The device is equipped with potentiometers to adjust lighting time and light intensity.



**Nominal voltage:**

230V~, 50Hz



type

**Type of sensor:**

Infrared



**Adjustable time setting (TIME):**



**Installation:**

flush mounting



**Detection range:**

9m



X°

**Detection angle:**

160°



**Adjustable daylight sensor (LUX):**

## General information

**Max. load:** 300 W

**Max. load of the LED light source:** 75 W

**Nominal voltage:** 230V~, 50Hz

**Relay output:** no

**Presence detector:** no

**Colour:** white

**Dimensions of the sensor - width (mm):** 86 mm

**Installation:** flush mounting

**Dimensions of the sensor - height (mm):** 86 mm

**Dimensions of the sensor - depth (mm):** 26 mm

**Working temperature:** -20°C~+40°C

**Degree of protection (IP):** 20

**Detection angle:** 160°

**Type of sensor:** Infrared

**Detection range:** 9 m

**Adjustable daylight sensor (LUX):** yes

**Daylight sensor adjustment range (LUX):** <3—2000lux

**Adjustable time setting (TIME):** yes

**Lighting time adjustment range (TIME):** min: 10 sek. ± 3 sek.; max: 7 min. ± 2 min.

**Adjustment of motion detection range (SENS):** no