

Motion sensor for installation box 160°, IP20

Marka: Orno | Symbol: OR-CR-261 | Ean: 5900378654742

ORNO

PRODUCT DESCRIPTION

This motion sensor is used to automatically control lighting or other electric appliances. It operates based on a two-wire system and can be flush-mounted inside an installation box of Ø60 mm diameter. The device is equipped with potentiometers to adjust lighting time and light intensity.

TECHNICAL DATA

General information:

Max. load:	300
Max. load of the LED light source:	75 W
Degree of protection (IP):	20
Relay output:	Yes
Nominal voltage:	230V~, 50Hz
Presence detector:	No
Colour:	white
Installation:	flush mounting
Dimensions of the sensor - width (mm):	86 mm
Dimensions of the sensor - height (mm):	86 mm
Dimensions of the sensor - depth (mm):	26 mm
Working temperature:	-20~+40
Detection angle:	160°
Dimensions of the mounting hole:	Ø60 mm
Type of sensor:	Infrared
Detection range:	9 m
Adjustable daylight sensor (LUX):	Yes
Daylight sensor adjustment range (LUX):	<3–2000lux
Adjustable time setting (TIME):	Yes
Lighting time adjustment range (TIME):	min: 10 sek. ± 3 sek.; max: 7 min. ± 2 min.
Adjustment of motion detection range (SENS):	No



