

Wireless driveway alert system with sound and light alarm, IP44, 300m, can be extended up to 16 sensors (and 4 zones).

୍ର

憻

**(1)** 

ORNO

Marka: ORNO Home | Symbol: OR-MA-716 | Ean: 5908254805585



## **PRODUCT DESCRIPTION**

The PIR motion sensor sends a radio signal to the receiver which then activates sound alarm, to inform that a motion has been detected in the protected area, and displays a number of the zone where the motion has occurred. Learning function with 4 zones supports up to 16 sensors (4 sensors per zone). IP 44 protection level allows to install the sensor outdoors and in rooms of increased humidity.




## **TECHNICAL DATA**

## General information:

Device even the of the transmittent	7 ٨٨٨\/
Power supply of the transmitter:	3 x AAA V
Max. power of the transmitter:	< 10mW
Doorbell volume (db):	80 dB
Type of transmission:	wireless
Nominal voltage:	3 x AA / 5VDC power supply
Dimensions of the transmitter - width (mm):	60 mm
Colour:	white
Possibility of extension:	Yes
Dimensions of the transmitter - height (mm):	130 mm
Loudness control:	Yes
Dimensions - depth:	39 mm
Dimensions of the transmitter - depth (mm):	52 mm
Battery included:	No
Number of ringtones:	35
Dimensions - width:	105 mm
Dimensions - height:	105 mm
Optical indication:	Yes
Detection angle:	120°
Transmission range:	300
Protection rating of the transmitter:	IP44
Max number of sensors:	16
Detection range:	8 m







0













