

## Code lock with touch keypad, proximity tags/cards reader and fingerprint reader, IP68, 1 relay output (1A)

Marka: **ORNO Home** | Symbol: **OR-ZS-822** | Ean: **5908254810275**



### PRODUCT DESCRIPTION

The standalone code lock combines the function of a touch access control keypad, proximity card and tag reader and fingerprint reader. This modern device works with electromagnetic locks, which use an access control system. It can also control other electrical or alarm devices. The lock has 1 relay output. Authorized persons may enter the room or building after reading the card, entering the access code or scanning the previously saved fingerprint. Non-volatile EPROM memory stores stored codes and parameters in the memory in the event of a power failure. Robust and extremely resistant housing for changing weather conditions. The

lock is suitable for surface mounting. Bright LED diodes indicate the operating status of the keypad. Two tags (OR-ZS-890) and two proximity card (OR-ZS-892) included.

## TECHNICAL DATA

### General information:

Touch keyboard:	No
Doorbell button:	No
Type:	Code lock
Operating mode:	fingerprint / card / pin code
Degree of protection (IP):	68
Type of transmission:	wired
Number of relay outputs:	1
Nominal voltage:	12V DC
Load capacity:	1A
Max. number of users:	10000
Installation:	surface mounting
Dimensions - depth:	24 mm
Proximity reader:	Yes
Dimensions - width:	70 mm
Keypad:	Yes
Dimensions - height:	140 mm
Frequency:	125 kHz
Temporary access can be granted:	No
Permanent access can be granted:	No
Backlight:	Yes
Fingerprint reader:	Yes

